

Selectone


ST-139 APPLICATION NOTE #1420

FOR USE WITH: **E.F. JOHNSON SDL & PPL SERIES**

APPROVAL DATE: 09JUL98S BY:RTs

CONNECTIONS
TONE UNIT

RADIO



All other wires are NOT used.

MODIFICATIONS
TONE UNIT

RADIO

USER: No Modifications Required.

SDL Series:

Make certain "A" to "B" Call Guard jumper is in, and solder the BLK/YEL wire from tone unit to this jumper. If retrofitting an SDL which had previously been installed with DCG you may find male connector pins at "A" and "B". The connector on the ST-138EFJ should only contact pins 1 thru 6 of the Call Guard connector

PPL Series:

Solder BLK/YEL wire from tone unit to pin 2 of the Mic connector. Clip out test point J209 to avoid short circuit to tone board.

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE

SELECTONE INC. • 3501 BREAKWATER AVE. HAYWARD, CA. 94545-1610 • (510) 781-0376
(800) 227-0376 • FAX (510) 781-5454 • E-Mail admin@selectone.com