

SELECTONE APPLICATION NOTE

Connections

TONE UNIT		RADIO	
<u>ST-120</u>		<u>J906 G.E. CENTURY II</u>	
WHITE/ORANGE	DECODE LATCH	4	
BROWN	MONITOR/RESET	5	
RED	+ SUPPLY	8	
BLACK	- SUPPLY	9	
GREEN	TONE INPUT	10	
NOTES		MODIFICATIONS	
		TONE UNIT: PLACE JU1 CENTER TO 'B'. USE WHITE/VIOLET AND BLACK/ORANGE WIRES AS REQUIRED. REMOVE AND JUMPER VR1.	
		RADIO: USE G.E. "CHANNEL GUARD" TYPE HOOKSWITCH.	
This is a recommended installation procedure for SELECTONE equipment based on the best information available to us at the time of publication; however, SELECTONE assumes no responsibility for the accuracy of the information or for any damage to the radio, tone unit, or other associated equipment resulting from the use of this procedure.			

RADIO MODEL:	G.E. CENTURY II
TONE MODEL NO.	ST-120
DESCRIPTION	BURST TONE DECODE
APPROVED	JFO 2/29/84
APPLICATION NO.	1196
	JNS