

Selectone

ST-120 APPLICATION NOTE #1210

FOR USE WITH: G.E. PHOENIX, PHOENIX S & SX APPROVAL DATE: 25JUL85 BY: JFO

=====

CONNECTIONS

TONE UNIT

RADIO

TONE UNIT	RADIO
	Interconnect board
(+) SUPPLY (RED)	J920
(-) SUPPLY (BLACK)	J906-9 A-
TONE INPUT (GREEN)	J906-1 FLTRD VOL/SQ HI
MONITOR/HOOK SWITCH (BROWN)	J906-5 <u>MON/RESET</u> (HOOK SW) NOTE 2,3
DECODE LATCHED (WHT/ORG)	J906-4 RX MUTE
DECODE MOMENTARY (WHT/VIO)	J906-12 EXTERNAL RELAY CONT NOTE 4
	Display board
LAMP (-) (BLK/ORG)	JU2-2 <--- <----> JU2-1 ---/\/\/\---> To A+ 220 Ohm NOTE 5
SET (WHITE)	

=====

MODIFICATIONS

TONE UNIT

RADIO

USER: NONE

1. The ST-120 installs similar to a TYPE 99 DECODER.
2. Install a jumper between HL60 and HL7.
3. The HOOK SW closes to A- to MONITOR.
4. This lead may be used to operate a horn relay.
5. Disp. Bd. R8, & Int. Bd. R911 **MUST** be removed to use this LED.

FACTORY: NONE

=====

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE

SELECTONE INC. • 3501 BREAKWATER AVE. HAYWARD, CA. 94545-1610 • (510) 781-0376
(800) 227-0376 • FAX (510) 781-5454 • E-Mail admin@selectone.com