

Selectone

ST-120 APPLICATION NOTE #1292

FOR USE WITH: Motorola Micor Base (Burst tone access rprr)

APPROVAL DATE: 07OCT88 BY: WDC

CONNECTIONS		RADIO		
TONE UNIT		PIN	BOARD	SIGNAL
(+) SUPPLY	(RED)	12	STATION CONT. MOD.	A+
(-) SUPPLY	(BLACK)	1	STATION CONT. MOD.	GND
MONITOR/HOOK SWITCH RST.	(BROWN)	8	SQLCH. GATE MOD.	SNGL. TN.
DECODE LATCHED	(WHT/ORG)	3	STATION CONT. MOD.	KEY INHIBIT
DECODE MOMENTARY	(WHT/VIO)	NC		
LAMP (-)	(BLK/ORG)	NC		
SET	(WHITE)	NC		

MODIFICATIONS		RADIO		
TONE UNIT				
USER: CUT R24 JU1=B JU3=SHORT				
FACTORY:				

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE

SELECTONE INC. • 3501 BREAKWATER AVE. HAYWARD, CA. 94545-1610 • (510) 781-0376

(800) 227-0376

• **FAX (510) 781-5454** •

E-Mail admin@selectone.com