

Selectone

ST-139 APPLICATION NOTE #1415

FOR USE WITH: G.E. CUSTOM MVP

APPROVAL DATE: 27MAY98S BY: RTS

CONNECTIONS
TONE UNIT

RADIO

ST-956MVP Application Cable		J906 SYSTEM/AUDIO/SQUELCH BOARD	
8	MONITOR (BLK/BRN)	S702-2	NOTE 1
10	P.T.T. (ENCODE ENABLE) (BLK/YEL)	H17	PTT (on S A S Board)
4	DECODE (-) (WHT/ORG)	5	Rx Mute
1	HI PASS FILTER OUTPUT (WHT/BLU)	2	From Tone Rej Fltr
11	HI PASS FILTER INPUT (BLUE)	3	To Tone Rej Fltr
12	TONE INPUT (GREEN)	4	Vol/Sq Hi
13	ENCODE OUTPUT (WHT/GRN)		J902-9 C.G. Input (on Tx exciter)
3	(+) SUPPLY (RED)	6	10V Reg
9	(-) SUPPLY (BLACK)	1	A-
7	MONITOR (BROWN)		

Wire #'s 2,5, and 6 are not used.

MODIFICATIONS
TONE UNIT

RADIO

USER: CUT JU1

Remove R933(H1 to H2);
1. Jumper FL210-C1 to S702-2 & 3
(this provides for front panel
monitor switch operation) using
spare wire supplied.

The BLK/BRN, YELLOW, and
WHT/GRN wires are flying leads.
Splice the BROWN wire to the BLACK
wire.

FL210 is a "bank" of feed-thru
capacitors in the rear of the
radio near J1. Refer to LBI 30163
page 9, mechanical parts, view
'Z'.

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE

SELECTONE INC. • 3501 BREAKWATER AVE. HAYWARD, CA. 94545-1610 • (510) 781-0376
(800) 227-0376 • FAX (510) 781-5454 • E-Mail admin@selectone.com