

# Selectone

**ST-139**

**APPLICATION NOTE # 1425**

**FOR USE WITH : Midland Model 70-335**

DATE: 6MAR99 / #5086 BY: JFO

## CONNECTIONS

Note	Pin #	ST-xxx Function	Wire Color	Host Radio Connection
	3	(+) Supply	Red	7
	9	(-) Supply	Black	13
	11	Hi Pass Filter Input	Blue	<b>Junction R116 and C133</b>
	1	High pass Filter Output	Wht/Blu	<b>Junction R116 and C132</b>
2	12	Tone Input	Green	3
3,4,5	13	Encode Output	Wht/Grn	6
	6	PTT (+)	Yellow	8
	10	PTT (-)	Blk/Yel	N/C
	7	Monitor (+)	Brown	<b>J502-3</b>
	8	Monitor (-)	Blk/Brn	N/C
	5	Decode (-) (- to Mute)	Blk/Org	N/C
	2	Hi Pass Filter Mute	Violet	N/C
	4	Decode (+) (+ to Mute)	Wht/Org	14

### Notes:

1. Unless otherwise indicated, the HOST RADIO connections refer to the 14 in line holes normally used for the tone option.
2. JU1 MUST be OPEN.
3. Set R4 to maximum.
4. JU4 MUST be OPEN.
5. Use VR452 in the radio to set the Tx CTCSS Level.
6. Remove JP-5 & R116 in the radio