

Selectone

ST-809 APPLICATION NOTE #8192

FOR USE WITH : MOTOROLA GP300/P110 APPROVAL DATE: 16JAN98S BY:RTS

CONNECTIONS

ANI UNIT			RADIO
(3)	(+) SUPPLY INPUT	RED	JUNCTION OF U404-8 AND C421
(9)	(-) SUPPLY INPUT	BLACK	P1-8 GND
(12)	RX SIGNAL INPUT	GREEN	P1-7 UNMUTED FLAT RX AUDIO
(13)	TRANSPOND TONE	WHT/GRN	P1-4 OPTIONAL TX AUDIO
(6)	PTT INPUT	YELLOW	NO CONNECTION
(10)	PTT OUTPUT	BLK/YEL	JUNCTION PB403 AND C468
(5)	DECODE MONENTARY	BLK/ORG	NO CONNECTION
(2)	CALL LAMP #1	VIOLET	JUNCTION OF Q411 AND R496
(4)	DECODE LATCH	WHT/ORG	JUNCTION OF PB401 AND C466
(8)	NO CONNECTION	BLK/BRN	NO CONNECTION
(7)	MONITOR	BROWN	JUNCTION PB402 AND C467
(11)	CALL LAMP #2	BLUE	JUNCTION Q411 AND R496
(1)	ALERT TONE	WHTBLU	JUNCTION OD C437 AND R465

NOTES: Program the radio so the opt2 is programmed to none. Program rx squelch type toTPL and select a dummy ctcss code. Program Mon/reset to GND to monitor (4130#), Call Lamp Steady (32000#). Decode Latch OFF=mute (4150#)

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE

SELECTONE INC. • 3501 BREAKWATER AVE. HAYWARD, CA. 94545-1610 • (510) 781-0376
(800) 227-0376 • FAX (510) 781-5454 • E-Mail admin@selectone.com