

Selectone

ST-809A/B APPLICATION NOTE #8212

FOR USE WITH :DR-130/430

APPROVAL DATE: 990508R*A BY: CPE

CONNECTIONS

DECODER UNIT			RADIO	
(3)	(+) SUPPLY INPUT	RED	CN2-6	13V
(9)	(-) SUPPLY INPUT	BLACK	CN2-1	GROUND
(11)	CALL LAMP #2	BLUE	N/A	
(1)	ALERT TONE	WHTBLU	CP12	
(12)	DTMF SIGNAL INPUT	GREEN	JUNCTION OF R30 AND R31	
(13)	TRANSPOND TONE	WHT/GRN	CN2-7	MIC
(6)	PTT INPUT	YELLOW	J201-2	PTT
(10)	PTT OUT	BLK/YEL	J201-2	PTT (SEE NOTES)
(7)	MONITOR/RESET	BROWN	JUNCTION OF S201 AND IC201	
(4)	DECODE LATCH	WHT/ORG	JUNCTION OF R58 & R80	
(5)	DECODE MOMENTARY	BLK/ORG	N/A	
(8)	N/A CALL LAMP #1	BLK/BRN	N/A	
(2)	RS-232 INPUT	VIOLET	N/A	

NOTES:

RADIO: TO RESET DECODER PRESS THE SHIFT KEY.

ST-809A/B:

PROGRAM "MUTE" OFF TO MUTE .

PROGRAM "HOOK SWITCH POLARITY TO GROUNDED OFF HOOK.

FOR THE RADIO KILL MODE ONLY, OPEN THE PATH OF PTT & PUT THE PTT IN & PTT OUT IN SERIES.

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE

**SmarTrunk Systems, Inc. • 23278 Bernhardt Street Hayward, CA. 94545 • Phone: (510) 887-1950
Fax:(510) 887-4011 • Website: www.selectone.com • E-Mail: technicalsupport@smartrunk.com**