

SELECTONE APPLICATION NOTE

Connections

TONE UNIT		RADIO
<p>BROWN MONITOR/RESET</p> <p>WHITE SET</p> <p>GREEN TONE INPUT</p> <p>WHITE/ORANGE DECODE LATCH</p> <p>BLACK/ORANGE CALL LAMP</p> <p>RED + SUPPLY</p> <p>BLACK - SUPPLY</p>	<p><u>NEUTEC SM1645H</u></p> <p>Mic CONNECTOR PIN 3</p> <p>COLLECTOR Q216</p> <p>J102 (EITHER SIDE)</p> <p>IC102-13</p> <p>P608</p> <p>J101-1</p> <p>GROUND</p>	
NOTES		MODIFICATIONS
		<p>TONE UNIT: PLACE JUI CENTER TO 'A', USE WHITE/VIOLET WIRE AS REQUIRED.</p>
		<p>RADIO:</p>
<p>This is a recommended installation procedure for SELECTONE equipment based on the best information available to us at the time of publication; however, SELECTONE assumes no responsibility for the accuracy of the information or for any damage to the radio, tone unit, or other associated equipment resulting from the use of this procedure.</p>		

APPLICATION NO.	1199
APPROVED	J.S. 6-13-84
DESCRIPTION	BURST TONE DECODE
TONE MODEL NO.	ST-120
RADIO MODEL:	NEUTEC SM1645H
	JNS