

# Selectone

## ST-200 APPLICATION NOTE #2131

FOR USE WITH: G. E. Progress Line

APPROVAL DATE: 14FEB89 BY: WDC

=====

### CONNECTIONS

TONE UNIT

RADIO

-----

(+) SUPPLY	(RED)		A426-J1
(-) SUPPLY	(BLACK)		A426-J20
TONE INPUT	(GREEN)		A426-J9
MONITOR/HOOK SWITCH	(BROWN)		J443-18
DECODE LATCHED	(WHT/ORG)		A426-J11
DECODE MOMENTARY	(WHT/VIO)		USER SUPPLIED HORN
LAMP (-)	(BLK/ORG)		USER SUPPLIED CALL LAMP
SET	(WHITE)		NOT USED

-----

### MODIFICATIONS

TONE UNIT

RADIO

USER:

REPLACE Q4 WITH A 1N914 DIODE.  
CATHODE TO COLLECTOR, ANODE TO BASE.

REMOVE AND JUMPER VR1.

NOTES:

A426 is the IF AUDIO SQUELCH board.  
Ensure that P/J443-18 is connected  
to P/J703-24, and this to P/J1-24,  
and this to P/J701-8, and this to  
the hang up box.

=====

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION.  
SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE

**SELECTONE INC.** • 3501 BREAKWATER AVE. HAYWARD, CA. 94545-1610 • (510) 781-0376  
(800) 227-0376 • FAX (510) 781-5454 • E-Mail admin@selectone.com